



# LED Mini Moonbeam



LED Disco Light fitted with 64 x LED 5mm

Code: VIS071 (Black)

## INSTRUCTION MANUAL

**Specification:**

64 x LED's 5mm (4xRed, 28xGreen, 20xBlue and 12xwhite)

Power Inlet: 240v 50Hz

Mains Inlet: cabled

Power Consumption: 10watt

Sound Activation: built in microphone



2.

**The rear of the unit: -**



**Getting started.**

Switch the unit on and the LED's will illuminate. The unit has pre-programmed patterns and by selecting various dipswitch settings you have control.

Dipswitch settings as follows:-

Effect	Control Mode	Control switch (ON)
1	Sound animation of pre-programmed patterns	Dipswitch 9 <b>ON</b> All others <b>OFF</b>
2	Chase of built-in patterns	All dipswitches in <b>OFF</b> position
3	Speed control of chase patterns	Selecting switches 1-8 into the <b>ON</b> position will speed up the chase

**Troubleshooting:**

**No power**=- check mains voltage is correct, and outlet switched on, check fuse

**Overheating/ cutting out**- ensure adequate ventilation

Dimensions: 220mm length, 140mm width, 100mm height (200mm c/w bracket)

**Importers and Distributors: -**



**Contact Details:** - Website: [www.batmink.co.uk](http://www.batmink.co.uk) E-mail: [info@batmink.co.uk](mailto:info@batmink.co.uk)